

Infiniti Orbital K/M 6050



Infiniti Orbital K/M 6050

Items	Specifications
Model	Infiniti Orbital K/M 6050
Operating System	Genuine Windows® 7 Professional
Chipset*	AMD 785G
Processor	AMD Sempron 140 AMD Athlon II X2 215, 240, 245, 250 AMD PHENOM II X2 545, 550 AMD PHENOM II X3 700 e, 710, 715, 720, 740 AMD PHENOM II X4 805, 810, 820, 910, 925, 945
System Memory	Support of unbuffered DDR3 800/1066/1333 MHz w/o ECC. Maximum expandibility of 16 GB in 4 DIMM slots
Video Graphics	ATI radeon HD4200 onboard graphics subsystem
IDE Channel	1XUDMA 66/100/133 channel
Hard Disk Drive	SATA Interface, 5 SATA ports, 300 mbps
Other Devices	16X DVD ROM, 22X SATA DVD Writer
Network Interface	Realtek RTL8111DL PCI-Express Base 1.0a Gigabit Ethernet Controller
I/O Ports	PS/2 Keyboard or Mouse-1, RJ 45 - LAN port-1, VGA Port-1, USB Port (2.0)-6 , Serial Port-1, Parallel Port-1, HDMI-1, E-SATA-1, DVI-1
Expansion Slots	2*PCI slots, 1*PCIEx1, 1*PCIEx16
Power Supply	200 Watts & Above
Audio	Integrated 8 Channel Realtek ALC888S Audio
Keyboard & Mouse	HCL PS/2 Mechanical/Internet/Membrane/Bilingual Keyboard, HCL PS/2 2 Button Scroll /Optical Mouse
Monitors	Choice of HCL TFT-LCD Monitors 15.6" or above
Manageability	HCL Desktop Manageability Software
Multi Level Security	Sys Admin / Usr Password Change, Enabling / Disabling Serial Port, Parallel port and USB port
Industry Compliance	DMI 2.4, ACPI 2.0
Certificate	MS Windows® 7. Suse Linux

*Some Windows 7 features such as Windows Touch and watching and recording live TV may require advanced or additional hardware. Check <http://windows.microsoft.com/systemrequirements> for details.



 Windows 7

more details :

E-mail : infiniti@hcl.in

Phone : +91-120-2555109

HCL